ScanPod3D www.scanpod3d.com

USOL and USOL-DUO 3D Laser Foot Plantar Scanner2025.01.01Small and light. Reliable after years of field use worldwide.Fast true 3D laser scan. Auto landmark, measurement, and analysis.Custom shoes and orthotic insoles fabrication for foot clinics.Prefab shoes and orthotic insoles selection for retail stores.

USOL/USOL-DUO vs. LSR/LSR-DUO: Smaller/Lighter/Faster/Prettier



USOL/USOL-DUO Software UI more elegant



If 2 round blue markers are placed on 1st Met and 5th Met before scanning, USOL software identifies the two markers.

USOL/USOL-DUO Features (New)

More measurement metrics More accurate Arch Index More elaborate PDF report Direct to FTP sending file after Save Double-Scan mode: Relaxed/Corrected for Before/After compare Scan Modes allow exposure value change Customize PDF report format Automatically identify 2 met points if blue markers are placed Much more reliable hardware design Much easier repair/replacement of parts (on-site) Foldable heel camera with laser on USOL Heel camera without laser on USOL-DUO Front vertical toe laser help align foot/ankle Supports normal scan speed with low-cost CPU WeChat/Facebook integration (to be finished...)

Customize software logo, sell your own brand

For programmers: CMD/TCP call scanner to receive data-

-integration into your own CAD software and database

Customize RX form for custom shoe/insole

Custom top plate and side panel design

Encrypt scanners to lock files

USOL/USOL-DUO Features (carried over from LSR/LSR-DUO)

Auto analysis for arch type, hallux, and heel (manual) Mark landmarks on foot then drag points to match Foot report with manual annotations Export to STL/WRL, JPG/PNG, PDF report, CSV data files FTP send order to orthotic insole/shoe fabrication Change interface language to your local language

©Copyright 2025 Vismach Technology Ltd. All rights reserved. Content subject to change without notice. Subject to Disclaimer, Warranty, and Software License Agreement.

	USOL(New)	LSR	USOL-DUO(New)	LSR-DUO
Foot/Foam Box/Plaster Cast	Yes/Yes/Yes	Yes/Yes/Yes	Yes/Yes/Yes	Yes/No/No
Foot: Non/Full/Semi-Weight	Yes/Yes			
Indoor Lighting Conditions	Yes, no darkroom or shielding required. But should avoid direct sunlight.			
3D Accuracy	Clean 3D Mesh. +/-1.0mm. USOL/USOL-DUO has better 3D resolution.			
3D output file STL/WRL	Yes/Yes. WRL supports color texture on 3D file.			
Color Texture (Round-Trip)	Yes. A unique feature not found on other 3D foot scanners.			
Heel Camera/Heel Laser/Toe Laser	Yes/Yes/Yes	Yes/Yes/No	Yes/No/Yes	No/No/No
Size (mm) / Weight(Kg)	490*230*69 / 4.7	600*265*89 / 7.0	490*440*69 / 7.7	600*515*8.9 / 11.0
Scan Volume (mm)	330*140*80	350*140*70	330*140*80 X2	350*140*70 X2
Load Capacity	180 Kg			
Minimum CPU				
Normal Speed Scan	Atom Z8350 (2.9 sec)	I5-6200U (2.9 sec)	Atom Z8350 (2.9 sec)	I5-6200U (2.9 sec)
High Speed Scan	I5-6200U (1.9 sec)	No Support	I5-6200U (2.2 sec)	No Support
Minimum RAM	4G	4G	4G	4G
USB Port 2.0 or 3.0	Yes	Yes	Yes	Yes
Windows 7/8/10	No/No/Yes. Win10 only	Yes/Yes/Yes	No/No/Yes. Win10 only	Yes/Yes/Yes
Power Supply (adapter)	100~240V 50/60HZ AC to DC 12V/3.0A. Worldwide compatible. Major country plug types are provided.			
Warranty (Limited)	1 Year (per warranty statement)			

USOL/USOL-DUO Configurations

USOL Standard: Scanner, Power Adapter, USB Cable (White), Foot Switch, Heel Camera (folding with laser). **Same as LSR standard config. USOL Floor:** USOL Standard + Toe Laser, Side Steps (Pair).



USOL Standard USOL Floor USOL Vertical: USOL Standard + Toe Laser, Folding Frame (with wheels) and VESA Bracket.



USOL Vertical: Folding Frame (wheels) and VESA Bracket Mounting position for supine or prone Height adjustable 500-1000mm, chair to recliner Heel Camera records heel position Heel and Toe laser help to control foot posture

USOL-DUO Standard: Scanner, Power Adapter, USB Cable (White), Foot Switch. **Same as LSR-DUO standard config. USOL-DUO Floor**: USOL-DUO Standard + Toe Laser, Heel camera (no laser).







USOL-DUO Standard

USOL-DUO Floor

USOL-DUO Floor

USOL-DUO Floor

©Copyright 2025 Vismach Technology Ltd. All rights reserved. Content subject to change without notice. Subject to Disclaimer, Warranty, and Software License Agreement.